

MyRedFlare
SARWATCH SMS COMMAND SUMMARY

ARM SARWATCH with NEW PLAN

SMS: ***pwd arm n intentions***
 where... *pwd* = your SMS password
n = number of hours from now (range 1-240).
intentions = your plan description (150 chars)
 Note: System Armed with Alert Time of *n* hours from the next "o'clock" hour, and message replaces any existing plan you may have set.
Returns: Confirmation message with Alert Time in your local time.

ARM SARWATCH with EXISTING PLAN

SMS: ***pwd arm n***
 where... *pwd* = your SMS password
n = number of hours from now (range 1-240).
 Note: If you had already armed Sarwatch your Alert Time is reset to *n* hours from the next whole "o'clock" hour.
Returns: Confirmation message with Alert Time in your local time.

EXTEND ALERT TIME

SMS: ***pwd arm n***
 where... *pwd* = your SMS password
n = number of hours from now (range 1-240).
 message = text description of your plan (max 150 chars)
 Note: System Armed using existing plan you may have entered using the website (i.e. detailed plan, flightnote etc) but had not yet armed.
Returns: Confirmation message with Alert Time in your local time.

DISARM SARWATCH

SMS: ***pwd disarm***
 where... *pwd* = your SMS password
 Note: Always disarm before Alert Time to prevent Alert Messages being sent to your Trusted Contacts.
Returns: Disarmed confirmation message.

REQUEST SARWATCH STATUS MESSAGE

SMS: ***pwd status***
 where... *pwd* = your SMS password
Returns: Sarwatch system status (Armed/Disarmed, Disarm By etc)

ADD MESSAGE OR POSITION TO EXISTING PLAN

SMS: ***pwd add message***
 where... *pwd* = your SMS password
 message = any message you want to add to your existing Sarwatch plan (max 154 characters).
 Note: The message is added, along with the current time, to the description field in your current plan. Your Alert Time, if set, is unchanged.
Returns: Confirmation message with system status info.

LOCATION UPDATE

SMS: ***pwd loc location***
 where... *pwd* = your SMS password
 location = text location data, e.g. address, or country, or GPS latitude longitude.
 Note: If possible, MyRedFlare will determine your new timezone from this data, if you have changed timezones, so that Sarwatch will operate in your Local Time.
Returns: Confirmation message, with status and timezone info.

SOS – TRIGGER ALERT NOW!

SMS: ***pwd sos [message]***
 where... *pwd* = your SMS password
 message = optional text to be added to the Alert Message sent to your Trusted Contacts.
 Note: Triggers Sarwatch Alert Messages to your Trusted Contacts are sent NOW, rather than waiting for your Alert Time. If Sarwatch was not armed, a brief Alert Message will still be sent including your message.
Returns: NO CONFIRMATION MESSAGE (i.e. silent response)
 If you want a confirmation, follow this command with a separate "STATUS" SMS command.

"TM OK" (ALERT CANCELLATION) MESSAGE

SMS: ***pwd ok [message]***
 where... *pwd* = your SMS password
 message = optional text, such as a brief reason why you failed to disarm Sarwatch in time.
Returns: Acknowledgement/Advice message.
 Note: If you fail to disarm Sarwatch before your Alert Time then you will receive an "Alert Messages Sent" message from us, advising that your Trusted Contacts have been sent messages. You must send this "OK" message to cancel the Alert, or cancel using the website. We will then send an Alert Cancellation message to your Trusted Contacts.

NOTE ABOUT YOUR SMS PASSWORD:
Your SMS password, which you can choose or change on your Profile page of the MyRedFlare website, is an identification security measure. It should be different from your website password and can be as short as 3 characters. It must be sent at the start of every SMS command.

CHANGE YOUR MOBILE/CELLPHONE NUMBER

SMS: ***pwd setnum email password***
 where... *pwd* = your SMS password
email = your email address
password = your MyRedFlare password
 Can also be set from website DETAILS page.
 Number must not be in use by another user.
 Must be set so that MyRedFlare can identify you when you send other SMS commands.
Example: *pwd setnum blogs@example.com secretword*
Returns: Acknowledgement message (cost 1 credit)

CHANGE LOCAL TIME/COUNTRY TIMEZONE

SMS: ***pwd time xxx***
 where... *pwd* = your SMS password
 xxx = 3- or 4- letter country/timezone code for new country (see World Times on MyRedFlare website for codes) or UTC/GMT offset for new timezone.
 e.g. the timezone for Singapore can be set by sending either "time SIN" or "time UTC+8". This sets the local time to be used for your Sarwatch notifications.

Send SMS command messages to one of our SMS Contact Numbers:

- AUSTRALIA: +61429100704
- UK: TBA
- USA: TBA
- SOUTH AFRICA: TBA

Note: You must include the "+" sign. You do not have to be in the same country to access these numbers... your SMS will be sent internationally if necessary.

